



www.selectses.com

Cellular-Based Select Gate Series Entry System



STANDARD FEATURES

- ◆ Gate Control via SMS (Short Message Service) Text, Select Gate Mobile Control App, Keypad, Remote Touch Tones, Card Readers or Transmitters (Optional)
- ◆ 10 Phone Number Capacity (dialed via keypad)
- ◆ 1000 Caller ID Recognizable Phone Numbers
- ◆ Call Forward to 3 Rollover Phone Numbers in Programmed Sequence
- ◆ 2000 Mix & Match Pins / Transmitters / Cards
- ◆ Pin Code Range from 0001 to 9999
- ◆ Card Number Range from 00001 to 65534
- ◆ Site Code Range from 001 to 255
- ◆ Overhead LED lights for easy viewing at night
- ◆ Blue back lit keypad for the ease of reading
- ◆ Latch Open Gate via SMS Text, Mobile App or Remote Touch Tones
- ◆ Hold Gate Open 1 Hour via SMS Text, Mobile App or Remote Touch Tones
- ◆ Built-in 26 Bit Wiegand Input for Card Access
- ◆ REX (Request to exit) Input
- ◆ Gate Position Sense Input
- ◆ Signal Strength verifier via SMS Text
- ◆ Optional Plug-in RF Rceiver for use with any SES SelectPass Transmitters. (Model: SG3DMRCL)

SGMC MOBILE APP
Available on the App Store and Google Play
For use with Entire Select Gate Series Product Line
See Mobile App Information for Specifics



SG3DMCL

SPECIFICATIONS

- ◆ **Mounting dimensions:**
SG3DMCL 7" H x 10" W x 6" D
- ◆ **Construction:**
Back box: .090 aluminum, primed and painted black texture for exterior use.
Face plate: stainless steel
- ◆ **Power Input:**
12-24V AC/DC (16.5V 20VA AC Transformer Included)
- ◆ **Current Draw:**
90mA @ 12VDC; 80mA @ 24VDC
- ◆ **Operating Environment:**
Temperature -20 F to +140 F, Relative Humidity 5% to 95% non-condensing.
- ◆ **Relay Output (2):**
Form C dry contact, 24 V @ 3 AMPS.
- ◆ **Mounting:** Surface or Pedestal.
- ◆ **Memory Type:** non-volatile.
- ◆ **Tone Detection:**
Crystal controlled capable of detecting 100 mS. DTMF tone, (detects touch tones only).
- ◆ **Shipping Weight:**
Approx. 15 lbs. for SG3DMCL only, actual shipping weight dependent on final system configuration.

SG3DMCL compatible with AT&T, T-Mobile and other GSM carriers SIM Cards, if uncertain which network you are using please check with your service provider; Good mobile GSM coverage with high signal strength is recommended for trouble free installation. SGMC Mobile App can be used with GSM and CDMA carriers



www.selectses.com

Cellular-Based Select Gate Series
Entry System



STANDARD FEATURES

- ◆ Gate Control via SMS (Short Message Service) Text, **Select Gate Mobile Control** App, Keypad, Remote Touch Tones, or Card Readers
- ◆ 10 Phone Number Capacity (dialed via keypad)
- ◆ 1000 Caller ID Recognizable Phone Numbers
- ◆ Call Forward to 3 Rollover Phone Numbers in Programmed Sequence
- ◆ 2000 Mix & Match Pins / Cards
- ◆ Pin Code Range from 0001 to 9999
- ◆ Card Number Range from 00001 to 65534
- ◆ Site Code Range from 001 to 255
- ◆ LED lights for easy viewing at night
- ◆ Blue back lit keypad for the ease of reading
- ◆ Latch Open Gate via SMS Text, Mobile App or Remote Touch Tones
- ◆ Hold Gate Open 1 Hour via SMS Text, Mobile App or Remote Touch Tones
- ◆ REX (Request to exit) Input
- ◆ Gate Position Sense Input
- ◆ Signal Strength verifier via SMS Text
- ◆ Built-in 26 Bit Wiegand Input for Card Access

SPECIFICATIONS

- ◆ **Mounting dimensions:**
SG2CL 7" H x 9 7/16" W x 4 9/16" D
- ◆ **Construction:**
Back box: .090 aluminum, primed and painted black texture for exterior use.
Face plate: stainless steel
- ◆ **Power Input:**
12 - 24V AC/DC (16.5V 20VA AC Transformer Included)
- ◆ **Current Draw:**
90mA @ 12VDC; 80mA @ 24VDC
- ◆ **Operating Environment:**
Temperature -20 F to +140 F, Relative Humidity 5% to 95% non-condensing.

SGMC MOBILE APP
Available on the App Store and Google Play
For use with Entire Select Gate Series Product Line
See Mobile App Information for Specifics



SG2CL

- ◆ **Relay Output (2):**
Form C dry contact, 24 V @ 3 AMPS.
- ◆ **Mounting:** Surface or Pedestal.
- ◆ **Memory Type:** non-volatile.
- ◆ **Tone Detection:**
Crystal controlled capable of detecting 100 mS. DTMF tone, (detects touch tones only).
- ◆ **Shipping Weight:**
Approx. 15 lbs. for SG2CL only, actual shipping weight dependent on final system configuration.

SG2CL compatible with AT&T, T-Mobile and other GSM carriers SIM Cards, if uncertain which network you are using please check with your service provider; Good mobile GSM coverage with high signal strength is recommended for trouble free installation. SGMC Mobile App can be used with GSM and CDMA carriers.